

Inverter Power Cycle

To re-establish an internet connection to the SolarEdge Inverter conduct a power cycle of the inverter and networking components. To conduct this power cycle follow these simple steps:

1. Turn the red toggle switch to OFF
2. Turn the “DC Disconnect Switch” (the black power knob) below the Inverter to the OFF position.
3. Turn the solar circuit breakers in your main electrical (or sub) panel to the OFF position.
4. Wait ten to fifteen minutes for the inverter to fully power down.
5. Reboot/Restart your home internet router.
6. Turn the solar breakers back into the ON position
7. Turn the DC Disconnect Switch back into the ON position.
8. Turn the red toggle switch back into the ON position.

Note: After these steps have been performed, the inverter will begin to power up and the web communications should re-establish themselves. Please note that the production data is stored in your inverter’s internal memory and can take 24-48 hours to upload to the web for your visual production tracking.