



- Up to 16 Channels (limited to 60mbs)
- View up to 64 cameras**
- Linux or Windows Based OS (NX Server Software + Client)
- AMD Ryzen 3 3.2q
- 16gb DDR4 RAM
- 1x 120Gb SSD
- 4x 3.5" Drive Bays
- Radeon Vega Graphics
- Asus Prime A320M-K Motherboard
- 4x SATA 6Gb/s
- 1x HDMI (and 1x VGA)
- 4x USB 3.0 & 2x USB 2.0
- GBLAN
- Mic/Audio Port
- 3 Years Warranty



Specifications

Motherboard: Asus Prime A320M-K

Socket: AMD AM4
Internal Drive Form Factor: 3.5" Drive

Internal Drives Supported: 4

Max Memory: 32GB / 64 GB

Memory Type: DDT4-2400 / DDR4-3200

PSU: 400W

Processor: AMD Ryzen 3 3.2g

2M Cache, up to 3.3 GHz Asus Prime A320M-K

1x HDMI & 1x VGA

Displayes Supported: 2

USB Configuration: 2x front (3.0) & 4x rear

(2x 3.0 & 2x2.0)

Total SATA Ports: 4

Audio: Front; 1x Mic & 1x Audio Rear; 3 x Audio jack(s)

Integrated LAN: 1x Gigabit Warranty: 3 Years

Other Features:

Graphics:

Graphics Output:

Intel® Virtualization Technology for Directed I/O (VT-d)

Intel® HD Audio Technology

SDXC card slot Dual microphones

Maximum Capacity

To figure out your planned bit rate (up to 60mbs) please visit either;

www.vivotek.com/tools/design-tool

if using VIVOTEK + Smart Stream

nx.networkoptix.com/calculator/

for all other camera products

